# **Inverter Generators**

800, 1600, 2000 Watts





# A Honeywell inverter easily travels to wherever power is needed.

Compact and lightweight, it generates super clean power that's electronics friendly. Hosting a tailgate party or planning a camping trip? Include your Honeywell inverter to power appliances, TVs, or laptops and bring on the food, drink, and game highlights.



# Inverter Generators 800, 1600, 2000 Watts

Packing more power generation per pound than standard portable generators, Honeywell inverters are super-quiet, lightweight and fuel efficient.

# **FEATURES**

## **Really quiet:**

Because inverters are fully enclosed, the engine sound is reduced, making them the perfect portable answer for tailgaiting and camping. Inverter technology makes the Total Harmonic Distortion (THD) an incredibly low <3%.

### Easy to transport:

The compact units are incredibly lightweight, with the 800 Watt model weighing in at less than 30lbs. The builtin handle makes it easy to transport.

## Fuel efficient, exclusive EcoMode™:

Honeywell inverters feature EcoMode, which adjusts engine speed to meet demand. When power needs are low, the engine runs more slowly, resulting in a quieter, more fuel efficient unit.

### Control panel with status lights including:

### Engine protection

Low-oil shutdown detects low oil level and shuts the engine down to prevent potential engine damage.

### Electronic circuit breaker protection

Prevents damage from circuit overload.

### How does inverter technology work?

The clean power of a Honeywell inverter is possible because of inverter technology, which takes the raw power produced by the generator and passes it through an electronic microprocessor. The result is clean and stable power comparable to utility power, competely safe for computers and other sensitive electronic devices.



# SPECIFICATIONS

	800 Watts	1600 Watts	2000 Watts
Running Watts	800	1600	2000
Starting Watts	850	1650	2200
Engine Size	38cc	99cc	126cc
Engine Type	4 stroke Generac OHV	4 stroke Generac OHV	4 stroke Generac OHV
Low-oil Shutdown	Yes	Yes	Yes
Outlets	(2) 5-15R (1) 120V AC	(2) 5-15R (1) 12V DC (1) 120V AC	(2) 5-15R (1) 12V DC (1) 120V AC
Run Time @ 50% load	3.6 hours	4.9 hours	4.7 hours
12V battery charger	No	Yes	Yes
First Oil Included	Yes	Yes	Yes
Emission Certified	49 states	49 states	49 states
Warranty	2 Year Limited Residential 6 month Commercial	2 Year Limited Residential 6 month Commercial	2 Year Limited Residential 6 month Commercial
Dimensions (L x W x H")	18x10x15	21x11x18	22x12x18
Weight (lbs.)	27.5	47.3	49.6

To learn more, go to **honeywellgenerators.com** or call 1-855 -GENINFO (436-4636)

0192080HWL March 2011 © Generac Power Systems, Inc. All rights reserved. Specifications subject to change without notice.

The Honeywell Trademark is used under license from Honeywell International Inc.

Honeywell International Inc. makes no representation or warranties with respect to this product.



Generac Power Systems, Inc.

S45 W29290 Hwy. 59 Waukesha, WI 53187 1-855-Gen-Info (436-4636) honeywellgenerators.com